



SH

Brass shunts 1 A / 2000 A, 0.2  
accuracy class

The shunt is a passive component allowing DC current to be measured. When the shunt is calibrated with precision within a 0.2% accuracy class, measuring the voltage drop between its two terminals enables to calculate the exact current value going through the shunt. Our shunt can be used as reference resistor for our micro-ohmmeters and data acquisition systems.

## Description

The shunt is a passive component allowing DC current to be measured. When the shunt is calibrated with precision within a 0.2% accuracy class, measuring the voltage drop between its two terminals enables to calculate the exact current value going through the shunt. Our shunt can be used as reference resistor for our micro-ohmmeters and data acquisition systems.

## Specifications

Model	Range	Precision class	Voltage drop
<b>SH1</b>	1 A	0.2	100 mV
<b>SH2</b>	2 A		
<b>SH5</b>	5 A		
<b>SH10</b>	10 A		
<b>SH20</b>	20 A		
<b>SH30</b>	30 A		
<b>SH50</b>	50 A		
<b>SH100</b>	100 A		
<b>SH200</b>	200 A		
<b>SH500</b>	500 A		
<b>SH1000</b>	1,000 A		
<b>SH1500</b>	1,500 A		
<b>SH2000</b>	2,000 A		

Brass connection terminals:

- 2 'current' terminals to connect the shunt to the circuit
- 2 'potential' terminals to connect the shunt to the measuring instrument

Overload: 20% in normal operating conditions, 50% in short accidental regime

## Models and accessories

SH1	Shunt 1 A - 100 mV - 0.2 class
SH2	Shunt 2 A - 100 mV - 0.2 class
SH5	Shunt 5 A - 100 mV - 0.2 class
SH10	Shunt 10 A - 100 mV - 0.2 class
SH20	Shunt 20 A - 100 mV - 0.2 class
SH30	Shunt 30 A - 100 mV - 0.2 class
SH50	Shunt 50 A - 100 mV - 0.2 class
SH100	Shunt 100 A - 100 mV - 0.2 class
SH200	Shunt 200 A - 100 mV - 0.2 class
SH500	Shunt 500 A - 100 mV - 0.2 class
SH1000	Shunt 1,000 A - 100 mV - 0.2 class
SH1500	Shunt 1,500 A - 100 mV - 0.2 class
SH2000	Shunt 2,000 A - 100 mV - 0.2 class