

Conventional Photoelectric Smoke Detector **SLR-E3N**



Features

- Removable, High Performance chamber
- Remote Indicator output
- Wide voltage range (9.5 ~ 30 V dc)
- Low profile design with one piece outer cover
- Twin fire LEDs allow 360° viewing
- Range of mounting bases
- Approved by LPCB & VdS
- Also available in white and black

Description

The SLR-E3N is a Photoelectric Smoke Detector, which is fully compatible with the majority of existing Conventional systems.

The SLR-E3N incorporates Hochiki's unique High Performance photoelectric smoke chamber removing the need to use Ionisation Detectors in the majority of applications. An integral third terminal provides a remote indicator output.

The smoke chamber is easily removed or replaced for cleaning and utilises a unique baffle design which allows smoke to enter the chamber whilst keeping out ambient light.

Specification

Ordering Codes	Sensor	SLR-E3N SLR-E3N(WHT) SLR-E3N(BLK)
	Replacement Chamber	SLV/ALK REPLACEMENT CHAMBER
Operating Voltage	9.5 – 30 V dc	
Quiescent Current (typ)	35 µA	
Maximum Current Alarm	40 mA	
Remote Indicator Drive	20 mA (max) / 9.5 – 14 mA (typ)	
Operating Temperature Range	-10 °C to + 50 °C	
Storage Temperature Range	-30 °C to + 60 °C	
Maximum Humidity	95%RH - Non Condensing (at 40 °C)	
Ingress Protection Rating	IP42	
Colour / Case Material	Ivory, White or Black / ABS	
Weight (g)	95 (excluding base)	
Diameter (mm) / Height (mm)	100 / 38	
Compatible Bases	YBN-R/6 YBN-R/6SK	YBO-R/6R, YBO-R/6RS YBO-R/6RN, YBO-R/6PA
Base Fixing Centres (mm)	48 ~ 74	
Approvals	LPCB EN54: Part 7 VdS EN54: Part 7 (G208040)	