

Weight Indicator

FEATURES

- Works with load cells in weighing measurement systems
- Inputs: load cell – 4-wire or 6-wire; 1 x digital
- Outputs: 2 x relay; 1 x analog
- Data sheet or dead weight calibration
- Protection class IP 65
- RS-485 / Modbus RTU
- Signal peak value detection

APPLICATIONS

- Process Weighing


DESCRIPTION

The WIN 5 weight indicator is designed for operations with load cells in simple industrial applications. The indicator is equipped with operating pushbuttons that allow: tare weight setting; zero setting for empty balance; and displaying of gross and net weight values. The readouts of the measured mass are presented on a 6-digit LED display. The relay control outputs can adjust the level of measured signal and are controlled according to level value. The indicator's software allows the performance of two calibration methods: data sheet calibration or dead




weight calibration. Moreover, the indicator is equipped with analog current output. The indicator is available in 24 VDC or 230 VAC power supply.

CONFIGURATION



Weight Indicator

OUTLINE DIMENSIONS



SPECIFICATIONS

PARAMETER	VALUE	PARAMETER	VALUE
FRONT PANEL			
Display	LED, 6-digit, 13 mm height, red Values -999 to 9999 + two decimals Divisions max. 10 000d	ANALOG OUTPUT	
Keyboard	5 buttons for menu control and data entry	Current output	0–20 mA, 4–20 mA, max. 700 Ω resistive load
RELAY OUTPUT			
Number of relays	2 pcs	Resolution	13 bit
Relay type	Closing relay contacts	COMMUNICATION INTERFACES	
Contact data	1A/250 VAC	Modbus RTU, RS-485 (two wire)	
LOAD CELL INPUT			
Excitation	4.6 V ±10%, I _{max} 60 mA. Exc. – connected to earth	POWER	
Load cells connections	6-wire technique, min. resultant impedance of 80 Ω (e.g., 4 load cells 350 Ω)	Power supply	19–50 VDC / max. 4.5 W; 85–260 VAC / max. 4.5 VA, 50/60 Hz
Tare range	100% of selected range	Power supply output	24VDC +5%, -10% / max. 100 mA, stabilized
Input for full scale	2 mV/V or 4 mV/V	ENVIRONMENTAL AND MECHANICAL DATA	
DIGITAL INPUT			
Low level	0 V – 1 V	Temperature range	0 to +50°C
High level	10 V – 30 V (about 5.5 mA @ 24 V)	Connector type	Connector blocks with screw terminals
APPROVALS			
For details contact blhnobel@vpgsensors.com .			

BLH Nobel continuously seeks to improve product quality and performance. Specifications may change accordingly.

Disclaimer

ALL PRODUCTS, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE.

Vishay Precision Group, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "VPG"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained herein or in any other disclosure relating to any product.

The product specifications do not expand or otherwise modify VPG's terms and conditions of purchase, including but not limited to, the warranty expressed therein.

VPG makes no warranty, representation or guarantee other than as set forth in the terms and conditions of purchase. **To the maximum extent permitted by applicable law, VPG disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.**

Information provided in datasheets and/or specifications may vary from actual results in different applications and performance may vary over time. Statements regarding the suitability of products for certain types of applications are based on VPG's knowledge of typical requirements that are often placed on VPG products. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. You should ensure you have the current version of the relevant information by contacting VPG prior to performing installation or use of the product, such as on our website at vpgsensors.com.

No license, express, implied, or otherwise, to any intellectual property rights is granted by this document, or by any conduct of VPG.

The products shown herein are not designed for use in life-saving or life-sustaining applications unless otherwise expressly indicated. Customers using or selling VPG products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify VPG for any damages arising or resulting from such use or sale. Please contact authorized VPG personnel to obtain written terms and conditions regarding products designed for such applications.

Product names and markings noted herein may be trademarks of their respective owners.

Copyright Vishay Precision Group, Inc., 2014. All rights reserved.